

# AEGIS 4000RT <sup>PLUS</sup>

## RESIDENTIAL NON-SUBSCRIBER TELEPHONE ENTRY SYSTEM



- Install as an Intercom system on the existing phone line or dedicated phone line.
- Built-in 315MHZ Radio Receiver, included two transmitter
- Remote programming via a touch tone phone
- Distinctive Ringing and Call Waiting
- Two Relays
- Automatic Call Forwarding or Manual Call Forwarding
- 50 programmable access code
- Indoor or outdoor, surface mount.
- Brushed Stainless Steel Face-plate

### SPECIFICATIONS

**POWER INPUT:** 12VAC/40VA (supplied) or 12VDC/40VA  
**CURRENT CONSUMPTION:** 420 mA idle, 620 mA operating.  
**RADIO RECEIVER MEMORY CAPACITY:** 15 transmitter button codes per channel.  
**EMERGENCY BATTERY:** 12VDC 40VA with 12VDC 4.5Ahr battery must be used to power the system.

**OPERATING ENVIRONMENT:** -32°F to 140°F. Humidity 0%-95% noncondensing.

**MEMORY:** EEPROM (non-volatile).

**DIMENSIONS:**

Surface 9-1/8"(H) x 6-15/16"(W) x 3-7/8"(D).

**WARRANTY:** 24 Months

### ORDER PART NUMBER

4000RTP Surface mount system

### ACCESSORIES

**UPM1S** Standard Single Arm (42"H, 5"x5" base)  
**UPM4S** Standard Single Arm (47"H, 5"x5" base)  
**UPM1L** Large Single Arm (47"H, 8"x8" base)  
**UPM6L** Large Single Arm (64"H, 8"x8" base)  
**UPM8L** Large Single Arm (84"H, 8"x8" base)  
**UPM2** Double Vertical Arm (44"/84"H, 8"x8" base)  
**UPM5** Double Horizontal Arm (47"H, 8"x8" base)  
**UPMDB64** Single Arm Direct Buriel (64"H)  
**UPMDB72** Single Arm Direct Buriel (72"H)  
**UAP78** Adapter Plate AeGIS 8000P Series  
**UPM12E** 12" Expansion Arm use for all UPM  
**UAP64** Adapter Plate for mounting the AeGIS 4000RTP

**ARFR** Radio Frequency Receiver  
**ARFT** Radio Frequency Transmitter  
**ARFHT** Radio Frequency Handheld Transmitter.  
**UVPC** Color Camera Package  
**USP1** AC and Telephone Surge Protector  
**UBAT1** 12VDC 4.5 Ahr backup battery.

Specifications and Warranty subject to change without prior notice

PACH AND COMPANY  
Home of Telephone Access Control Systems

AEGIS ANTUM

Phone: 1-888-678-7224

949-498-2951

www.pach-co.com