

GV-Compact DVR V2 (GV-LX4C2 / GV-LX4C2V)



INTRODUCTION

The GV-Compact DVR is a mobile video recorder. It can simultaneously display real-time images from four cameras. For firmware V1.05, the recording frame rate of each channel is adjustable up to 30 / 25 fps at the resolution of 720 x 480 (NTSC) / 720 x 576 (PAL). For firmware V1.06, the recording frame rate of each channel is adjustable up to 30 / 25 fps at the resolution of 704 x 480 (NTSC) / 704 x 576 (PAL). You can access the four video channels either in the quad mode or single channel mode.

The Anti-Vibration model of the GV-Compact DVR has already been tested to withstand severe levels of shock and vibration in mobile environments. It is perfect to be installed in any vehicles, such as buses and vans, for surveillance and recording.

The special design of the GV-Compact DVR enables you to link up with TV, VGA and spot monitors simultaneously for direct display. The GV-Compact DVR offers many features that you can expect to have.

KEY FEATURES

- 4-channel video and audio recording and playback
- MPEG-4 compression
- Up to 720 x 480 (NTSC) / 720 x 576 (PAL) recording resolution for firmware V1.05; up to 704 x 480 (NTSC) / 704 x 576 (PAL) recording resolution for firmware V1.06
- Up to 120 images per second recording rate at D1 resolution
- Independent channel resolution, quality and frame rate settings
- Support one 3.5" or 2.5" SATA HDD (2.5" to 3.5" HDD converter required)
- Support two external USB HDDs
- On-screen menu and Web-based control
- Display video on TV, VGA and Spot Monitor simultaneously
- Continuous, motion and scheduled recording
- 4 alarm inputs, 4 relay outputs
- Retrieve video by date, time and event
- Motion detection function with 3 sensitivity values adjustable on each channel
- Video signal auto detection
- Remote playback
- Support USB DVD-RW for video backup
- GPS tracking (GPS module required)
- UMTS (UMTS module required)
- 3G Mobile Phone Surveillance
- Support central monitoring systems Center V2, VSM and Control Center
- Support geographic information system GV-GIS
- Vibration and mechanical shock protection
- Buzzer alarm on video lost, input trigger, motion detection and disk full
- Support 16 languages on web interface and 10 languages on OSD



MODELS



The GV-LX4C2V equipped with vibration absorbers, can withstand severe levels of shock and vibration in mobile environments.

Caution: The standard and anti-vibration models have different internal designs. It is forbidden to connect the standard model to the vehicle power supply.



SPECIFICATIONS

		GV-LX4C2 Standard Model	GV-LX4C2V Anti-Vibration Model	GV-LX4C2V Anti-Vibration ACC Model
Video				
Video Standard		NTSC, PAL		
Video Input/Output		4 Videos In, 4 Loops Out		
Compression		Geo MPEG4 (ASP)		
Frame Rate	NTSC	30 fps/ch at D1 resolution		
	PAL	25 fps/ch at D1 resolution		
	NTSC	704 x 480, 704 x 480 De-inter	lace, 352 x 240, 352 x 240 3GI	PP v7 (firmware V1.06)
\". \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \		720 x 480, 720 x 480 De-inter	lace, 360 x 240, 360 x 240 3GI	PP v7 (firmware V1.05)
Video Resolution	PAL	704 x 576, 704 x 576 De-inter	· · · · · · · · · · · · · · · · · · ·	,
		720 x 576, 720 x 576 De-inter	· · · · · · · · · · · · · · · · · · ·	· · · · · · · · · · · · · · · · · · ·
Video Streaming		Configurable frame rate and		,
Video Adjustment		Brightness, Contrast, Hue, Sa		
Audio		, , , ,		
Audio Input/Output		4 Audios In, 1 Audio Out		
Compression		G.723		
Output Signal Formats				
Danalastia.	VGA Out	800 x600, 1024 x 768, 1280 x	1024	
Resolution	TV Out	640 x 480		
V. Frequency	VGA Out	60Hz		
	TV Out	60Hz		
Management				
	Trigger	Time, Sensor Input, Motion D	etection	
Event Management	Action	Store video to HDD (AVI for	rmat)	
Event Management		 Central monitoring by Cen 	ter V2 and VSM	
		 Activate relay outputs to c 	ontrol external devices	
		Remote upgrade by Web browser		
Firmware Upgrade		 Use a USB flash drive 		
		Use the upgrade utility included on the Softwae CD		
			' (HDD converter required for	2.5" HDD from GeoVision)
Storage (Optional)		2 external USB HDDs		
		DVD RW backup		
Client PC Requirements		Microsoft IE 6.x or above run	ning on Windows XP/Vista/7/S	Server 2008



	Czech / Danish / English / French / German / Hebrew / Hungarian / Italian / Japanese / Polish / Portuguese / Russian / Serbian / Simplified Chinese / Spanish / Traditional Chinese		
_	English / French / German / Italian / Japanese / Portuguese / Russian / Simplified Chinese / Spanish / Traditional Chinese		
	• 802.11b/g, 802.11n Wireless LAN (optional)		
HTTP, TCP, UDP, SMTP, FTP,	HTTP, TCP, UDP, SMTP, FTP, DHCP, NTP, UPnP, DynDNS, Mulitcast, 3GPP/ISMA, RTSP, PSIA (firmware version 1.06)		
IP address filtering			
4 Videos In, 4 Audios In	4 Videos In, 4 Audios In		
1 TV Out, 1 Spot Out, 1 VGA	1 TV Out, 1 Spot Out, 1 VGA Out, 1 Audio Out, 4 Video Loops Out		
4 digital inputs, 4 relay outputs. RS-232 for GPS	4 digital inputs, 4 relay outputs, RS-485 for PTZ,		
none		1 port	
RJ-45, 10/100 Mbps	·		
2 ports			
1 port for optional External I	1 port for optional External IR Receiver		
12V, 5A (60W Max.)	5 ~ 36V, 5A (60W Max.)		
4 inputs			
4 outputs			
-20 ~ 50 ° C / 4 ~ 122 ° F	-20 ~ 50 ° C / 4 ~ 122 ° F		
5 ~ 85% RH (non-condensing	5 ~ 85% RH (non-condensing)		
3 3370 1111 (11311 331118			
176 x 253 x 105 mm / 7 x 10	x 4 in		
	Polish / Portuguese / Russian English / French / German / / Spanish / Traditional Chine • 10/100 Base-T Ethernet • 802.11b/g, 802.11n Wirel • Mobile broadband: UMTS HTTP, TCP, UDP, SMTP, FTP, PSIA (firmware version 1.06) IP address filtering 4 Videos In, 4 Audios In 1 TV Out, 1 Spot Out, 1 VGA 4 digital inputs, 4 relay output RS-232 for GPS none RJ-45, 10/100 Mbps 2 ports 1 port for optional External I 12V, 5A (60W Max.) 4 inputs 4 outputs	Polish / Portuguese / Russian / Serbian / Simplified Chin- English / French / German / Italian / Japanese / Portugue / Spanish / Traditional Chinese • 10/100 Base-T Ethernet • 802.11b/g, 802.11n Wireless LAN (optional) • Mobile broadband: UMTS, EDGE, etc. (optional) HTTP, TCP, UDP, SMTP, FTP, DHCP, NTP, UPnP, DynDNS, PSIA (firmware version 1.06) IP address filtering 4 Videos In, 4 Audios In 1 TV Out, 1 Spot Out, 1 VGA Out, 1 Audio Out, 4 Video Le 4 digital inputs, 4 relay outputs, RS-485 for PTZ, RS-232 for GPS none RJ-45, 10/100 Mbps 2 ports 1 port for optional External IR Receiver 12V, 5A (60W Max.) 5 ~ 36V, 5A (60W Max.) 4 inputs 4 outputs	

Note:

- 1. The GV-Compact DVR V2 cannot work with the microphone that acquires power from the unit. Use the microphone that has external power supply.
- 2. Product design and specifications are subject to change without notice.

Options

Optional devices can expand your GV-Compact DVR's capabilities and versatility. Contact your dealer for more information.

External IR Receiver	The external IR receiver, with a 5-meter cable (16.4 feet), allows long-distance remote control of the GV-Compact DVR.		
GV-GPS 232 Receiver	GV-GPS 232 Receiver, with RS-232 interface, is a Global Position System receiver. It can be applied to vehicle tracking and location verification.		
2.5" to 3.5" HDD Converter	The HDD converter allows you to install a 2.5" SATA HDD into GV-Compact DVR.		
GV-Relay V2	Working with this module, GV-Compact DVR can drive the loads of relay outputs over 5 volts.		
WiFi USB Adaptor	The WiFi USB Adaptor is designed to connect the GV IP devices, such as GV-Video Servers or GV-Compact DVRs, to the wireless network. This product complies with IEEE 802.11 b/g/n (Draft 3.0) standards for wireless networking.		
Power Adaptor of DC 12V,	The power adaptor is used to power on the Anti-Vibration Model of ACC Version to test the		
5.0A	connection.		



Supported Wireless LAN USB Adaptor

Vendors	Model
D-Link	DWA-140 (H/W version B1), DWL-G122 (version C1)
EDIMAX	EW-7318Ug, EW-7718Un
Linksys	WUSB54GC, WUSB600 (version 1)
Pegatron	WL-166N11
Note: Linksvs W	USB54GC ver. 3 is not supported.

Supported Mobile Broadband Device

Vendors	Model
HUAWEI	EC169C, E169, E220, E1692, E1750 USB Modem (HSDPA/UMTS/EDGE/GPRS/GSM)
	E1752 and E1756 (Firmware V1.06)
Novatel	MC950D, (HSDPA/UMTS/EDGE/GPRS/GSM)
	MC996D (Firmware V1.06)
ONDA	MSA523HS (Firmware V1.06)
Verizon	USB760 Modem (EVDO)
Vodafone	K3565 (Rev 2)