

Accessing the HDCVI Camera OSD

In order to access the on-screen display (OSD) menu on your HDCVI camera, you will set up your HDCVI DVR to control the camera. HDCVI allows you to control your cameras over the coaxial video cable without the need to run additional wires. The DVR provides this function utilizing the PTZ control function.

1. Connect the HDCVI Camera to your HDCVI DVR.

Twist on the BNC coaxial connector to the appropriate video port on the back of your HDCVI DVR.

2. Configure the PTZ Settings for the Camera Channel on your HDCVI DVR.

Within the DVR Main Menu, select Setting and PAN/TILT/ZOOM. Select the appropriate channel to which you have connected the HDCVI camera you wish to control. Within the **Control Mode** field, change the value to "HDCVI". Within the **Protocol** field, change the value to DH-SD1 and then press Save. Right click on the mouse to back all the way back out to you live view frames.

3. Use the PTZ Control Panel to Access the OSD on your HDCVI Camera.

Within the video frame of the camera you have configured to control, right click on your mouse and select **Pan/Tilt/Zoom**. Click on the **Page Switch** button until you reach the control panel that includes the Enter Menu and Exit Menu buttons. Click on the **Enter Menu** button to bring up the HDCVI camera OSD.

4. Configure your HDCVI Camera Options.

Use the directional control button to navigate up and down through the HDCVI Camera OSD menu options. To change the value of an option, use the right and left arrows on the directional control button. To enter a sub-menu (indicated on the OSD menu by the return symbol) press the **Enter** button on the PTZ control panel.

5. Exit the HDCVI Camera OSD Menu.

After your changes have been made, navigate to the **EXIT** option of the Main Menu. The default operation is to save the changes that you have made, but this may be changed by press the right arrow on the directional control button. Press the **Enter** button while on the EXIT option to finish your session.