

Color Bullet Camera

EV-1323CWP4

Includes:

- Concealed wiring
- All-metal case & sunshield
- Non-condensing coated glass

SECO-LARM's Color Bullet Camera provides a clear picture with good resolution at a low lux. The camera features a Sony 1/3" CCD chip with a 4.3mm lens. A specially-coated glass prevents condensation in order to extend the camera's life and ensure clear picture quality. Additional features include Auto Electronic Shutter, Auto Gain Control, Backlight Compensation, Auto White Balance, and concealed wiring.





FEATURES:

- ► Sony 1/3" Color CCD.
- Special non-condensing coated glass.
- High sensitivity, low lux. Use under most light conditions.
- Vertical aperture correction for video enhancement.
- Small, easy to install.
- Adjustable metal sunscreen.
- Concealed cable to prevent tampering.
- Anti-color-rolling technology reduces color rolling with flourescent lighting.
- Weatherproof design (IP66) for indoor or outdoor use.

SPECIFICATIONS:

| Туре | Color Bullet Camera |
|------------------------|--------------------------------------------------------------------------------|
| Chip | 1/3" Sony CCD |
| Resolution | 420 TV lines horizontal |
| Pickup elements | 512 x 492 pixels |
| Sync | Internal |
| Video output | 1 Vp-p composite output, 75 Ohms. |
| Lens | 4.3mm |
| Minimum illumination | 0.1 Lux, F1.2 |
| Backlight compensation | Automatic |
| Shutter control | Auto, 1/60~1/100,000 sec. |
| Gain control | Automatic |
| Gamma correction | 0.45 |
| White balance | Automatic |
| S/N ratio | Over 48dB |
| Power source | 12VDC (+/-10%) |
| Current drain | 150mA |
| Storage temperature | $-22^{\circ} \sim 140^{\circ} \text{F} (-30^{\circ} \sim 60^{\circ} \text{C})$ |
| Operating temperature | $14^{0} \sim 113^{0}$ F (- $10^{0} \sim 45^{0}$ C) |
| Dimensions | 0.87" x 3.07" (22 x 78 mm) |
| Weight | 3.2oz (90g) |
| | |

HDBulletCam.pmd

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.