

PRO2000 Wireless Security System

Now you can offer your customers complete home security and home automation all in one inexpensive and easy-to-install package!



PRO2000 VP (7piece value pack)

- Quick and easy installation
- Fully supervised
- Open 4+2 data format
- Line seizure
- Home automation
- Up to 16 Wireless sensors. Any combination of Door/Window or Motion detectors
- Up to 16 Wireless remotes. Any combination of Keychain or Handheld remotes or emergency pendants.

INSTALLATION IS A SNAP! - All door/window sensors and remote controls register with the control panel at the touch of a button. The control panel is programmed by selecting the desired options (delays, central station phone numbers, home automation features, etc.) on a one-page setup screen and down-loading into the panel. This can be accomplished by your choice of one out of three options: either in the customer's home with a laptop computer, in your office with your desktop computer or remotely via modem. The basic system pictured above can easily be installed in less than 1 hour.

FULLY SUPERVISED! - All installed door/window sensors and motion detectors establish a signal with the control panel every 90 minutes to verify connection. If, during any continuous four hour period, a connection is not established, the control panel will indicate a trouble condition both by visual zone indicator and audible signal.

HOME AUTOMATION! - The PRO2000 has built-in home automation controls and is fully compatible with all X-10 PRO home automation modules. Open up a new world of home control to your customers (and a new profit center for your business!). The PRO2000 allows the homeowner to control anything from table lamps to garage doors all at the touch of a button. These features are normally found only on much higher priced equipment.

IS ANYONE HOME? - When the PRO2000 security system is armed in the away mode, a timer will automatically turn several lamp or appliance modules on or off at random time intervals, to give the home a lived-in look (and sound) for added security.

NO MORE FALSE ALARMS AT THE KEYPAD! (NO MORE KEYPAD!!!) - All system functions, including home automation features, can be operated from the remote controls. Convenient keychain remotes allow the customer to arm and disarm the system even from outside the home! Your customers don't want to fumble with keys or try to remember a set of numbers and now they don't have to. An added convenience is a feature that allows the homeowner to switch on an entrance light right from the car.

DIGITAL CONTROL COMMUNICATOR! - In the event of a break-in, the digital communicator will call the monitoring station and alert them as to which sensor has been tripped and the location of that sensor (e.g., door, window or motion detector). If an optional medical alert pendant is activated, the monitoring station will be alerted that an emergency medical condition is in effect.

ADVANCED SENSORS! - X-10 PRO Door/Window Sensors provide effective protection for doors and windows with long battery life. By adding extra magnetic switch pairs, you can also protect extra windows with one sensor. Sophisticated motion detectors with dual element passive infrared (PIR) technology combined with two-setting sensitivity adjustment ensures reliable protection.

PROLink! - The PROLink feature allows the PRO2000 to activate devices upon arming and disarming by sending a specific letter and number code. For example: The PRO2000 can set back the temperature control on the X-10 PRO Digital Thermostat (PDT10) when armed in "away" mode and return the temperature to normal when disarmed.

The PRO2000 is perfect for retrofitting any home under 2,000 square feet, townhouses, condominiums and apartments. Elimination of keypad and hard-to-remember codes cuts down on false alarms and is a big selling point. If you've ever considered getting into home automation this is an easy and very inexpensive way to make the transition!

PRO2000VP Standard Components



Security Console
(PRO2000)



Keychain Remote
(PKR02)



Handheld Remote
(PSR01)



Door/Window Sensor
(PDS01)




Motion Sensor
(PMS01)



Lamp Module
(PLM01)

PRO2000 Optional Components




Powerhorns
(PSH01, PSH02)



Repeater
(PSX01)



Emergency Pendant
(PPR01)



Wall Switches
(XPS3, XPD3, PLW01)



Appliance Module
(PAM01, 2 PIN)
(PAM02, 3 PIN)



New Timer
(PHT02)

Specifications of PRO2000VP Standard Components

Security Console PRO2000

Power Supply: 120vac, 60 Hz
Standby Battery Time: 20 hours
Telephone Signalling: DTMF
RF Frequency: 310 Mhz
RF Range: 100 feet
Alarm Level @ 1m: 95 dB

Keychain Remote PKR02

Power Supply: 3v (2 x AAA)
Battery Run Time: 1 year
Output: 1mW
RF Frequency: 310 Mhz
RF Range: 100 feet
65,536 unique codes

Handheld Remote PSR01

Power Supply: 6v (4 x AAA)
Battery Run Time: 1 year
Output: 1mW
RF Frequency: 310 Mhz
RF Range: 100 feet
65,536 unique codes

Door/window Sensors PDS01

Power Supply: 3v (2 x AA)
Battery Run Time: 1 year
Output: 1mW
RF Frequency: 310 Mhz
RF Range: 100 feet
65,536 unique codes

PIR Motion Detector PMS01

Power Supply: 6v (4 x AAA)
Battery Run Time: 1 year
Output: 1mW
RF Frequency: 310 Mhz
RF Range: 100 feet
65,536 unique codes

Lamp Module PLM01

Power Supply: 120 V.A.C., 60 Hz
Rating: 300W
Incandescent dimmer with AGC circuit. Capacity to dim or brighten. Responds to "all lights on".



FCC
Approved



For more information call or visit our WEB Site

Tel.: 813-265-2888 • Toll free 800-411-2888 • Fax 813-265-1011 • E-mail: x10pro@aol.com

Tech support 800-TECH 003 (800-832-4003) • Web Site: <http://www.x10pro.com>

24 HR. FAXBACK SERVICE (813) 265-1420