



**VIDEO MASTER
AUDIO/VIDEO 4-INPUT
SEQUENTIAL SWITCHER
MODEL RVSS4AUD**

REVERE INDUSTRIES

REVERE INDUSTRIES • 1101 BIENVILLE STREET • NEW ORLEANS, LA 70112
504 523-3503 • 800 843-8321 • 24-HOUR FAX ORDER LINE 800 511-1821

SPECS AT A GLANCE

Power Source	110 VAC
Power Consumption	10 Watts Max
Video Inputs	Video (4): 1.0Vp-p 75 Ohms Terminating
Video Output.....	Video Monitor 1.0Vp-p 75 Ohms
Audio Circuit	200mV (4 Input/1 Output)
Audio Connectors	RCA Connectors
Frequency Response.....	10MHz $\pm$ 2 dB
Crosstalk Input to Input.....	Better than 40dB
Switching Interval	2 to 30 Seconds
Video Connectors	BNC Connectors
Position Indicator	LED Digital Display



DESCRIPTION

The RVSS4AUD is a 4-position Audio/Video Sequential Switcher with numeric display, a 3-position selector switch and a unique “audio follow” feature that automatically sequences audio and video simultaneously. The Center position permits one monitor to display the output of the remote cameras in automatic sequence. The Home position allows the operator to interrupt the sequence and view the output of the selected camera, while displaying the camera number on the LED display. The Bypass position drops the camera out of the sequence order.

