

U.C.R.M

UNIVERSAL 26 BIT WIEGAND - RS485 MODULE



- 26 Wiegand to RS485 module for all Quantum models, AeGIS 9000P Series and NPB9000P Series
- Compatible with UWCR (26 Bit Wiegand Reader) or most other manufacturers 26 Bit Wiegand Reader
- Up to 8-32 UCRM can be interfaced with the models above, contact us for more detail
- Single relay • Invisible installation in wall or any hidden location
- Audible tone and LED indicator for valid and invalid access
- Independent access, **ONLY** for Quantum models
- Stainless Steel faceplate
- Tamper Proof Screws
- Indoor or outdoor

Availability 3rd quarter 2011

24 months warranty

TECHNICAL SPECIFICATION

POWER INPUT: 12VAC 40VA or 12VDC 2 Amps (12VAC is supplied by Pach & Company).

CURRENT CONSUMPTION: 50mA Idle, 475mA operation.

EMERGENCY BATTERY: 12VDC, 4Ahr rechargeable (customer supplied).

COMMUNICATION: RS-485 (maximum distance not to exceed 4000 ft, daisy chain connection).

OPERATING ENVIRONMENT: 0°F to +140°F. Relative Humidity 0% to 95%.

RELAY OUTPUT: From C Dry Contact 120VAC 10A/ 24VDC 10 A/ 250VAC 7A with 5 seconds output duration.

MOUNTING: Surface, Indoor or outdoor

CONSTRUCTION: 16 Gauge Cold Rolled Steel with Brushed Stainless Steel Faceplate.

DIMENSION: 6-1/8" (H) x 7-1/16" (W), 1-1/2" (D)

SHIPPING WEIGHT: 5 lbs.

ORDERING PART NUMBER

UCRM

USCR OPTIONS AND ACCESSORIES

UWCR 26-Bit Wiegand Reader

Specifications subject to change without prior notice

PACH AND COMPANY
Home of Telephone Access Control Systems

A.E.G.I.S. QUANTUM

Phone: 1-888-678-7224

949-498-2951

www.pach-co.com