

## Product information

### OpenBAT-R - BAT-RUSWW9ACCF9B07T1T999ZH09.00.5103

Industrial Ethernet:Industrial Wireless LAN:Chassis:OpenBAT:OpenBAT-R	
<a href="https://www.e-catalog.beldensolutions.com:443/link/57078-24455-49859-24497-202741-379256/en/BAT-RUSWW9ACCF9B07T1T999ZH09.00.5103/uistate">https://www.e-catalog.beldensolutions.com:443/link/57078-24455-49859-24497-202741-379256/en/BAT-RUSWW9ACCF9B07T1T999ZH09.00.5103/uistate</a>	
Name	OpenBAT-R
	
	Rugged wireless LAN access point and/or client for use in industrial environments. Robust metal housing for mounting on DIN rails.
<b>Delivery informations</b>	
Availability	available
<b>Product description</b>	
Description	Rugged wireless LAN access point and/or client for use in industrial environments. Robust metal housing for mounting on DIN rails.
Port type and quantity	RJ45 LAN combo port: 10/100/1000BASE-TX, 1000BASE-SX/LX; LAN port 10/100BASE-TX RJ45 jack
Radio protocol	IEEE802.11a/b/g/h/n WLAN interface as per IEEE802.11n, up to 450Mbit/s gross bandwidth.
Type	BAT-RUSWW9ACCF9B07T1T999ZH09.00.5103
Order No.	BAT-RUSWW9ACCF9B07T1T999ZH09.00.5103
Supported Radio Standards	1st WLAN interface as per IEEE802.11n; 2nd WLAN interface as per IEEE802.11n
<b>More Interfaces</b>	
Ethernet	RJ45 LAN combo-port: 10/100/1000BASE-TX, 1000BASE-SX/LXLAN port 10/100BASE-TX RJ45 socket
Power supply/signaling contact	1 x terminal block, 2-pin; 1 x terminal block, 2-pin
V.24 interface	Configuration interface (COM) AT modem connection For automatic P2P connections verified over V.24 (train carriage coupling) Serial gateway for WLAN or virtual COM interface via WLAN
USB interface	1 x USB to connect the AutoConfiguration Adapter ACA21-USB
<b>Radio technology</b>	
Antenna connector	Reverse SMA socket, 3 x MiMo antenna connectors, 3 x MiMo antenna connectors
Range	Depends on type of antenna, frequency range and data rate. Use the BAT-Planner for planning your wireless network.
Frequency band	Supports 2.4 GHz and 5 GHz: 2400 -2483.5 MHz (ISM) and 5170 -5850 MHzSupports 2.4 GHz and 5 GHz: 2400 -2483.5 MHz (ISM) and 5170 -5850 MHz
Modulation	22M0F7D (DSSS/OFDM) at 2.4 GHz20M0G7D (OFDM) at 5 GHz
Encryption	IEEE 802.11i / WPA2 with passphrase or 802.1x and hardware-accelerated AES, closed network, WEP64, WEP128, WEP152, user authentication, 802.1x /EAP, LEPS, WPA1/TKIP. Please refer to the HILCOS data sheet for further information.
<b>Power requirements</b>	
Operating voltage	Voltage Range 1: 24/36/48 VDC (18-60 VDC); Voltage Range 2: 24/36/48 VDC (18-60 VDC)
Current consumption	17.5 W
<b>Ambient conditions</b>	
Operating temperature	-40 °C ... 70 °C
Note	Temperature of the surrounding air.
Storage/transport temperature	-40 °C ... 85 °C
Relative humidity (non-condensing)	10 % ... 95 %
MTBF	58 years (MIL-HDBK-217F)
Protective paint on PCB	No
<b>Mechanical construction</b>	
Dimensions (W x H x D)	150 mm x 136 mm x 115 mm
Mounting	DIN Rail
Protection class	IP30
<b>Approvals</b>	
Safety of information technology equipment	EN 60950-1 ,
Radio	FCC; EN 301 489-1, EN 301 489-17
<b>Scope of delivery and accessories</b>	
Scope of delivery	Device, Installation user manual, CD/DVD with manual, Terminal cable, 2 x 50 Ohm terminators, 6 x per WLAN module 3-dBi dipole dual-band antennas, 2 x 2-pin terminal block for signal contact, 2 x 2-pin terminal block for the working voltage.
Accessories to order separately	External antennas; external surge protection; cables 2 m, 5 m, 15 m. Some countries does not allow all Antennas. For more information please have a look into the Hirschmann Antenna Guide; wall mount plate

For more information please contact:

**Hirschmann Automation and Control GmbH**

Stuttgarter Strasse 45-51

72654 Neckartenzlingen

Germany

Phone: +49 7127/14-1809

E-Mail: [inet-sales@belden.com](mailto:inet-sales@belden.com)

The information published in the websites has been compiled as carefully as possible. It is subject to alteration without notice in technical as well as in price-related/commercial respect. The complete information and data were available on user documentation. Mandatory information can only be obtained by a concrete query.