

CONFIGURATION TUTORIALS



SETTING UP THE IMAXCAMPRO RECORDING

REGULAR 24-HOUR RECORDING

- 1. Right click on the live view of the recorder and log into the main menu of the recorder.
- 2. In the main menu navigate to Storage in the bottom row.
- 3. Next select Schedule on the left-hand side menu
- 4. Click on the Cogwheel (settings buttons) next to Sunday.
- 5. In the Settings menu click on "Regular" for Period 1. Then copy to all days at the bottom of the menu.
- 6. Save the Settings Menu
- 7. Once the settings menu closes all the bars for each day will be green. Use the copy button at the bottom of the screen to copy these settings to all channels.
- 8. Last apply and save.

MOTION RECORDING

- 1. Right click on the live view of the recorder and log into the main menu of the recorder.
- 2. In the main menu navigate to Storage in the bottom row.
- 3. Next select Schedule on the left-hand side menu
- 4. Click on the Cogwheel (settings buttons) next to Sunday.
- 5. In the Settings menu click on "MD" for Period 1. Then copy to all days at the bottom of the menu.
- 6. Save the Settings Menu
- 7. Once the settings menu closes all the bars for each day will be yellow. Use the copy button at the bottom of the screen to copy these settings to all channels.
- 8. Last apply and save.
- 9. Next navigate to the "Record" menu on the left-hand side of the screen.
- 10. In the Record menu make sure that Mainstream is set to record on Auto/Schedule, Sub Stream is set to stop, and that Snapshot is set to off.
- 11. Next navigate to Event at the top of the screen then to Video Detect on the left-hand menu and then to Motion Detection.
- 12. In the Motion detection menu make sure that "Enable MD" is check on, then under the Region "Set" button that the full screen is selected and that the sensitivity is set to 80 and threshold is set to zero. Last check and make sure that the "Record channel" is set to record the channel that settings are being set for. DO NOT use the copy button on this menu. Set each camera one at a time.
- 13. Last apply and save.