



6160V

Custom Alpha Display Keypad with Voice Annunciation and Message Center

The 6160V Custom Alpha Display Keypad with Voice Annunciation and Message Center is easy to install and simple to use. Audible system status and zone information messaging takes the guesswork out of operating a security system. Customers can also use the 6160V to record and play back voice messages.

The attractive white console blends with any décor, and features a contoured, removable door that conceals illuminated soft-touch keys. The oversized function keys remain easily accessible even when the keypad door is closed.



FEATURES AND BENEFITS

- Speaks system status and zone information
- Zones and system events displayed
- Family message center
- Large, easy-to-use keypad with bright 32-character display
- No confusing blinking lights
- Four programmable function keys
- Keys continuously backlit for visibility
- White with removable door blends with any décor

SPECIFICATIONS

Physical:

5-5/16"H x 7-3/8"W x 1-3/16"D
(135mm x 190mm x 30mm)

Wiring:

- **(Black):** Ground
- + **(Red):** +12 V DC (Aux. Power)
- D1 (Green):** "Data in" to control panel
- D0 (Yellow):** "Data out" from control panel

Current:

Standby: 75mA
Activated: 190mA

Compatibility:

Compatible with all VISTA® Controls
Requires VISTA-15P/VISTA-20P for voice chime

ORDERING

6160V	Custom Alpha Display Keypad with Voice Annunciation and Message Center (Honeywell Home)
6160VC	Custom Alpha Display Keypad with Voice Annunciation and Message Center (Resideo)

For more information

www.resideo.com/pro



For more information
resideo.com

Resideo Technologies, Inc.

2 Corporate Center Drive,
Suite 100
P.O. Box 9040
Melville, NY 11747
1-800-645-7492

L/6160VD/D | 11/21
© 2021 Resideo Technologies, Inc.
All rights reserved.
The Honeywell Home trademark is used under license from Honeywell International Inc. These products are manufactured by Resideo Technologies, Inc. and its affiliates.