

CHANNEL VISION™

AB-904 4-Source 4-Room A-BUS® Kit

Channel Vision's AB-904 4-Source, 4-Room A-BUS Kit is an excellent whole-house music solution. It allows up to four different sources to be played in four different zones simultaneously, making it perfect for families with a variety of listening interests. Controlling your music is easy with the P-1044's source specific IR repeating which allows independent control of identical source components. The A0502 remote allows you to easily adjust the volume level on the AB-124 without leaving the comfort of your favorite chair.

AB-904 Includes:



(1) P-1044

4-Source, 4-Room A-BUS Matrix

(4) AB-124
4-Source Amplified Keypad



(4) IR-3001
Single Head IR Emitter



(1) A0502
Remote Control



(1) J-110 tool
Punch Down Tool

Specifications: (typical)

P-1044

Power Supply Voltage:

24VDC, 3.2A

Connectors:

Audio Inputs:

(4) RCA type (L/R Audio), (4) RJ-45

Keypad Outputs:

(4) RJ-45, (4) 110 punch down

IR Emitter Outputs:

(5) 3.5mm mono jacks (4 source specific and 1 common IR output)

Operating Temperature:

-10°C to +50°C

Wiring Requirements:

CAT5 or better

Dimensions:

7"W x 6.5"H x 1.5"D

AB-124

Operating Voltage:

24VDC

Cable Requirements:

CAT5 or better

Compatible Speaker Impedance:

6-8 ohms

IR Frequency Range:

30-60kHz

IR Sensor Range:

40'@40kHz, 25'@56kHz

Operating Temperature:

-10°C to +50°C

Dimension (Behind faceplate):

1.75" (W) x 2.875" (H) x 1.875" (D)

Specifications subject to change without notice.



234 FISCHER AVENUE • COSTA MESA, CA 92626
(714) 424-6500 □ (800) 840-0288 □ (714) 424-6510 fax
www.channelvision.com □ email: sales@channelvision.com