



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: B004-DUA2-K-R

### KVM Switch - 2-Port Compact DVI/USB KVM Switch w/Audio and Cable

#### Highlights



- Control 2 computers with a single DVI monitor, USB keyboard and USB mouse
- Switch ports via keyboard hot keys, pushbuttons or software (not required)
- Allows sharing of audio components between systems; listen to music from one computer while accessing another
- Compact design saves desk space
- (x2) 6ft USB cables and (x2) 6ft DVI + Audio KVM cable kits included
- Compatible with all major operating systems

#### Description

The B004-DUA2-K-R is a compact 2-Port DVI/USB KVM Switch with optional audio and microphone switching function. It allows you to access, control, boot and reboot two DVI- and USB-enabled multimedia computers from a single console (keyboard, monitor and mouse). The independent audio/mic switching function allows an uninterrupted audio experience - you can continue listening to audio even when you switch to the other computer. This KVM switch uses DVI technology for digital video signal transmission to reduce undesirable distortion from conventional analog/digital conversion. Both DVI Single Link digital video ( up to 1920x1200 ) and DVI analog video ( up to 2048x1536 ) are supported. It includes innovative, easy-to-use KVM Switcher Software for Windows and Macintosh platforms. A small client application facilitates your KVM switching operations such as computer selection, hot key sequence programming, auto-scanning, auto-scan delay time programming, independent or simultaneous audio/computer switching and more. Compatible with all major operating systems.

#### Applications

- Use this KVM switch when accessing two DVI- and USB-equipped computers with one monitor, keyboard and mouse.

#### System Requirements

- Console: DVI-I or DVI-D Monitor, USB Keyboard and USB Mouse
- Computers: DVI-I Monitor Port (P118-000 DVI-I to DVI-D Adapter is required for PCs with DVI-D ports) and USB Port
- Audio (Optional): Speakers with standard 3.5mm Connectors and a computer with 3.5mm ports
- Compatible with all major operating systems

#### Package Includes





- B004-DUA2-K-R Compact 2-port DVI Single Link USB KVM Switch with Audio
- Two 6 ft. DVI-I with 3.5mm Audio Cable kits and Two 6 ft. USB A-B cables (P118-000 DVI-I to DVI-D Adapter is required for PCs with DVI-D ports)
- CD-ROM with Software
- Owner's Manual with Warranty Information
- 5V, 2A AC Adapter

#### Features

- Fast, easy switching via keyboard hot keys, push buttons or software (not required)
- Plug-and-play setup - no software required
- Hot-swap capability allows easy addition or removal of computers without powering down the switch or other computers
- Speaker and microphone connections allow sharing of audio components between systems (standard 3.5 mm audio connections)
- Supports 2-Channel Stereo Audio
- Independent audio switching allows you to listen to audio from one computer while switching to the other computer

- Supports both DVI Single Link digital (up to 1920 x 1200) and DVI analog (up to 2048 x 1536) video resolutions
- Supports Microsoft® IntelliMouse® and the scrolling wheel on most mice
- Compact design saves desk space
- Compatible with all major operating systems
- Includes two, 6ft Cable Kits

## Specifications

| OVERVIEW  |  |
|---|--|
| # Of Users  | 1  |
| AC Adapter  | Input: 100-240V, 50/60Hz, 0.3A Output: 5V, 2A  |
| Port Control                                      | Push Buttons, Hotkeys, Software  |
| Max CPU   | 2  |
| IP Remote Access                                  | NO   |
| PHYSICAL  |  |
| Color   | Silver   |
| Style   | Desktop  |
| ENVIRONMENTAL                                     |  |
| BTUs  | 245.52   |
| CONNECTIONS                                       |  |
| Ports   | 2  |
| Included KVM Cable (Equipment Side) - Connector 1 | DVI-I (Male)   |
| Included KVM Cable (Equipment Side) - Connector 2 | <br>(x2) 3.5mm (Male)   |
| Included KVM Cable (Equipment Side) - Connector 3 | <br>USB A (Male)        |
| Local Console Ports - Port 1                      | DVI-I (Female)   |
| Local Console Ports - Port 2                      | <br>(x2) USB A (Female) |
| Local Console Ports - Port 3                      | <br>(x2) 3.5mm (Female) |
| CERTIFICATIONS                                    |  |
| Certifications                                    | FCC, CE, RoHS Compliant  |
| WARRANTY  |  |
| Product Warranty Period (Worldwide)               | 1-year limited warranty  |

## Related Items

### Optional Products

| Product Type               | Related Model                 | Description   | Qty. |
|----------------------------|-------------------------------|---|------|
| Audio Cables               | <a href="#">P312-006</a>      | 6-ft. Mini-Stereo Dubbing Cord (3.5mm M/M)                        | 1    |
| Audio Cables               | <a href="#">P312-010</a>      | 10-ft. Mini-Stereo Dubbing Cord (3.5mm M/M)                       | 1    |
| Audio/Video Cables         | <a href="#">P560-006-A</a>    | 6-ft. DVI Dual Link TMDS + Audio Cable (DVI-D M/M, 3.5mm M/M )    | 1    |
| Audio/Video Cables         | <a href="#">P560-010-A</a>    | 10-ft. DVI Dual Link TMDS + Audio Cable (DVI-D M/M, 3.5mm M/M)    | 1    |
| KVM Switches & Accessories | <a href="#">B004-DUA4-K-R</a> | KVM Switch - 4-Port Compact DVI/USB KVM Switch w/Audio and Cables | 1    |
| Video Cables & Adapters    | <a href="#">P118-000</a>      | DVI-D Male to DVI-I Female Adapter                                | 1    |
| Video Cables & Adapters    | <a href="#">P126-000</a>      | DVI Female to VGA Male Adapter (Analog DVI-F to HD15M)            | 1    |
| Video Cables & Adapters    | <a href="#">P556-006</a>      | 6-ft. DVI to VGA Cable (DVI Male to HD15 M)                       | 1    |
| Video Cables & Adapters    | <a href="#">P560-006</a>      | 6-ft. DVI Dual Link TMDS Cable (DVI-D M/M)                        | 1    |
| Video Cables & Adapters    | <a href="#">P560-010</a>      | 10-ft. DVI Dual Link TMDS Cable (DVI-D M/M)                       | 1    |
| Video Cables & Adapters    | <a href="#">P561-006</a>      | 6-ft. DVI Single Link TMDS Cable (DVI-D M/M)                      | 1    |
| Video Cables & Adapters    | <a href="#">P561-010</a>      | 10-ft. DVI Single Link TMDS Cable (DVI-D M/M)                     | 1    |
| Video Cables & Adapters    | <a href="#">P562-001-45L</a>  | 1-ft. DVI Dual Link 45 degree Left Extension Cable (DVI-D M/F)    | 1    |
| Video Cables & Adapters    | <a href="#">P562-006</a>      | 6-ft. DVI Dual Link Extension TDMS Cable (DVI-D M/F)              | 1    |

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.triplite.com/en/products/model.cfm?txtModelID=3692](http://www.triplite.com/en/products/model.cfm?txtModelID=3692).

Copyright © 2012 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.