

EB-300 Base Station

Description

Base station automatically displays a 6-digit identification code for any Talk-A-Phone 100-Series or 400-Series Emergency Phone. Base station functions as a standalone unit but also works in conjunction with Talk-A-Lert (Model **ETP-TAL**) to log and manage incoming calls.



Features

- Uniquely identify calling 100-Series and 400-Series Emergency Phones from any telephone with **EB-300**
- Indicates whether call was initiated by pushing button or by an auxiliary device, as well as which button of a 2-button phone initiated a call
- Built-in serial port for connection to a PC running Talk-A-Lert (Model **ETP-TAL**)
- Stores real time and date for processing

Specifications

Dimensions:	6.0(152) W x 2.25(57) H x 9.0(229) D in(mm)
Weight:	2.5 lbs. (1.1 kg)
Mounting:	Designed for desktop use
Wiring:	RJ11 ports for connection to telephone line and standard telephone Specialized DB9 serial port for connection to Talk-A-Lert PC
Power:	9VDC, 500mA power supply connects to 120VAC

Options & Accessories

Monitoring and Diagnostic Software: Model **ETP-TAL** automatically polls each emergency phone, reports incoming calls and keeps permanent records of all events