

On-Q

HA5201-WH

TV Display Interface - HA5201-WH

Turn any TV in the home into Unity Home System Interface with this single gang decorator strap.

Ships with IR Receiver, universal remote, and AV patch cable.



FEATURES

- Installs in any decorator plate and can be ganged with other home theater products behind the entertainment center.
- Simple push button interface to select desired input.
- Available sequencing of sources if desired.
- Mounts flush into the wall for a clean, out-of-the-way installation.
- Available in four attractive Studio colors. This attractive design complements the home and matches other On-Q devices in the [Studio design](#).

Ships with IR Receiver, universal remote, and AV patch cable.

Specifications

CONNECTORIZED INFO

Pinning:

1. 24VDC +/- 1.5V, .2A
2. Ground Power Ground

On-Q

HA5201-WH

3. Audio In + Audio Ground
4. Control Comm A RS-485 A
5. Control Comm B RS-485 B
6. Audio In - Unbalanced Audio, 2Vpp
7. Video Out+ TVDI Diff Video, 1Vpp
8. Video Out- TVDI Diff Video, 1Vpp

DIMENSION INFO

Product Weight U S: 1 lb

Overall Dimensions U S: Decorator Style Opening

GENERAL INFO

Color: White

Discontinued: No

TECHNICAL INFO

Storage Temperature: -55 to 75 Degrees Celsius

Humidity: Up to 95% RH (Non Condensing)

Material: ABS Plastic

IR Receive Frequency: 56K, 40 kHz Center Frequency, On-Q Burst Model

Power Requirements: +24 Vdc, +/-1.5 Vdc, 0.75 A max (via CM1010 LCD Module)

Mounting: Single Gang Decorator Strap

Cat5 Cable Rating: Cat 5e UTP, 4 Pair Solid Conductor (24 AWG)

Connection Method: Single RJ45