



FEATURES:

- Designed to Enable Full Operation of Prodigy DVRs
- Operates Most Major Brands of PTZ Utilizing Various Popular Protocols
- Easy to Operate 3-Axis Joystick
- Control up to 255 Devices via RS422/RS485 Communication

DVR FUNCTIONS:

COMMUNICATION	RS-422/RS-485
BAUDRATE	2400 ~ 9600bps
SETUP	Menu
CONTROL	REC, PlayBack, PTZ control

CAMERA FUNCTIONS:

COMMUNICATION	RS-485
BAUDRATE	Camera dependent
SETUP	Camera menu, Preset
CONTROL	P/T/Z, Preset, Tour

POWER:

POWER CONSUMPTION	2.2W
VOLTAGE	+4.5V ~ +5.5V
KEYPAD	40 KEY
DISPLAY METHOD	LCD, LED
TEMPERATURE	0° ~ 60°
HUMIDITY	10% ~ 75%
DIMENSIONS	11.81" x 1.97" x 5.79" (W x H x D)
WEIGHT	3.3Lbs. (1.5Kg.)