



KRAMER ELECTRONICS, Ltd.

www.kramerelectronics.com

VS-101AV

10x1 Composite Video & Stereo Audio Mechanical Switcher



The VS-101AV is a high-performance switcher for composite video and unbalanced audio signals. It switches any one of 10 composite video and unbalanced stereo audio signals to a single composite output.

FEATURES

- High Bandwidth - 500MHz (-3dB).
- Mechanical (Passive) Switching - No power required.
- Standard 19" Rack Mount Size - 1U.



VS-101AV

TECHNICAL SPECIFICATIONS

INPUTS:	10 video, 1Vpp/75Ω on BNC connectors; 10 unbalanced stereo audio, +4dBu typical, on RCA connectors.
OUTPUTS:	1 video, 1Vpp/75Ω on a BNC connector; 1 unbalanced stereo audio, +4dBu typical, on RCA connectors.
SWITCHING SYSTEM:	Mechanical, break-before-make, audio-follow-video mode.
BANDWIDTH (-3dB):	500MHz (video); 100kHz (audio).
CROSSPOINTS:	10 for video, 10x2 for audio, 1 set active at any given time.
SIGNAL LEVELS:	Up to 3Vpp video, +30dBu audio.
DIMENSIONS:	48.3cm x 10.2cm x 4.4cm (19" x 4" x 1U) W, D, H.
WEIGHT:	1.5kg (3.3lbs) approx.

