

AeGIS 7000 Series

MULTI-TENANT "DEDICATED PHONE LINE" TELEPHONE ACCESS CONTROL SYSTEMS



Full-flush Mount w/ Optional Ring

Surface Mount

FEATURES

- **Hands Free Multi Tenant Telephone Access Control Systems** from 25 to 250 tenants and 25 to 250 4-digit personal access codes.
- **Programming** local via system's keypad or remote via a touch-tone phone.
- Optional Radio Receiver.
- **Remote Access** press 9 to unlock door or optional radio transmitter.
- **Local Access** keypad entry code.
- Backlit Single Line Liquid Crystal Display (LCD) with Electronic Directory.
- **Postal Lock ready.**
- **Recess Keypad w/ Built-in night light,** available on surface mount only.
- **Support Voice Mail.**
- Brushed Stainless Steel or Brushed Brass Plating (special order only) Faceplate.
- Surface or full-flush mount. Outdoor or Indoor.

SPECIFICATIONS

Power Input: 12VAC 40VA (supplied) or 12VDC 40VA (output reading must be 13.5-14.5 VDC).

Current Consumption: 500 mA idle, 700 mA operating.

Emergency Battery: Built-in charging circuit for 12VDC, 4Ahr rechargeable battery (battery is not supplied).

Operating Environment: 32°F to 140°F.

Relative Humidity 0 % - 95 % noncondensing.

* Heater is required if the ambient temperature gets below 32°F

Single relay. Form C Dry Contact 120 VAC 10A, 24VDC 10A or 250VAC 7A.

Tone Detection: Crystal controlled detecting short bursts 80 ms.

Dialing: Touch-tone or pulse (programmable).

Incoming touch-tone through the microphone are ignored by the system.

Memory Type: EEPROM (non-volatile).

Construction: 16 Gauge Cold Rolled Steel back box with enamel finished and 16 gauge brushed stainless steel or Brushed Brass Plating Faceplate

Dimension Surface : 10-3/4 "(H) x 8-1/2 "(W) x 3-1/8 "(D)

Dimension Full-flush: 10-13/16"(H) x 8-3/8"(W) x 2-7/16"(D)

Dimension Full-flush Mounting Ring (FFM7 or FM7BZ):

Inside: 11-1/8" (H) x 8-11/16"(W) x 2-5/8"(D)

Outside: 14-5/16" (H) x 12-1/8" (W)

Mount: Surface and Full-flush (mounting ring is included). Outdoor or Indoor.

Shipping Weight: 11 Lbs. approximate.

"TWO YEARS WARRANTY" includes lightning and power surge if Pach and Company Surge Protector (ASP1) is installed.

ORDER PART NUMBER

SURFACE MOUNT BRUSHED STAINLESS STEEL FACEPLATE

7025 (25 tenants/25 access codes).

7050 (50 tenants/50 access codes).

7100 (100 tenants/100 access codes).

7150 (150 tenants/150 access codes).

7200 (200 tenants/200 access codes).

7250 (250 tenants/250 access codes).

SURFACE MOUNT BRUSHED BRASS PLATING FACEPLATE

7025BZ (25 tenants/25 access codes).

7050BZ (50 tenants/50 access codes).

7100BZ (100 tenants/100 access codes).

7150BZ (150 tenants/150 access codes).

7200BZ (200 tenants/200 access codes).

7250BZ (250 tenants/250 access codes).

FULL-FLUSH MOUNT BRUSHED STAINLESS STEEL FACEPLATE

7025FF (25 tenants/25 access codes).

7050FF (50 tenants/50 access codes).

7100FF (100 tenants/100 access codes).

7150FF (150 tenants/150 access codes).

7200FF (200 tenants/200 access codes).

7250FF (250 tenants/250 access codes).

FULL-FLUSH MOUNT BRUSHED BRASS PLATING FACEPLATE

7025FBZ (25 tenants/25 access codes).

7050FBZ (50 tenants/50 access codes).

7100FBZ (100 tenants/100 access codes).

7150FBZ (150 tenants/150 access codes).

7200FBZ (200 tenants/200 access codes).

7250FBZ (250 tenants/250 access codes).

OPTIONS AND ACCESSORIES

ARFR Radio Frequency Receiver.

ARFT Radio Frequency Transmitter.

ASP1 AC and Telephone Surge Protector.

AHP5 Heater Pad with Thermostat.

APM1 AeGIS Pedestal Mounting Post.

APM2 Double arm mounting base plate for auto, pedestrian and semi-truck.

APM3 Pedestal mounting post for semi-truck.

APM4 Pedestal Mounting Post with 45° arm.

APM5 Double arm side by side mounting base plate.

AP7 Adapter Plate for APM1, APM2, APM3, APM4 and APM5.

100DIR Paper Directory with built-in night light.

AVP7 AeGIS Black and White Video Package.

AVP7C AeGIS Color Video Package.

FFM7 Brushed Stainless Steel Full-flush Mounting Ring.

FM7BZ Brushed Brass Plating Full-flush Mounting Ring for 7000FBZ (special order only).

ABAT1 12VDC 4.5 Ahr backup battery.

ABAT2 12VDC 1.3Ahr backup battery.

Specifications subject to change without prior notice.



Pach and Company
www.pach-co.com

941 Calle Negocio
San Clemente, CA 92673

Phone: 1-888-678-7224
Fax: 949-498-6879