LECTUS enroll 5000 MD

www.boschsecurity.com





- ► Designed for reading Bosch coded MIFARE classic and DESFire EV1 credentials
- ▶ Simplifies enrollment process for operators
- ▶ Desktop reader with compact and robust housing
- ▶ Three LED indicators
- ▶ USB interface with long cable for more flexibility

This desktop enrollment reader reads the data record of Bosch coded MIFARE classic and DESFire EV1 credentials and provides the information to the respective host application.

This simplifies the cardholder management and avoids type errors. The reader is connected to an USB port of the operator's enrollment workstation. It is supported by the host applications Access PE and BIS Access Engine.

Certifications and approvals

1999/5/EC – Radio Equipment and Telecommunications Terminal Equipment R&TTE 2004/108/EC – EMC Directive

Technical specifications	
Technology:	MIFARE classic and DESFire EV1, data record of Bosch coded credentials
Environment:	Indoor use only

PC OS:	Windows 7, Windows 8
Signal Elements:	Three LEDs: Green: Contactless transponder successfully read, Yellow: Device ready, Red: Not successfully read
Housing unit:	Plastic (PC+ABS-FR)
Housing color:	RAL 7015 (slate gray)
Interfaces:	USB / Version 2.0
Techn. Data:	Storage temperature range: -30°C to +70°C Operating temperature range: -25°C to +60°C
Dimensions (L x W x H):	112 x 54 x 27 mm
USB Plug:	A Type
Power Supply:	via USB
Cable length:	approx. 2 meters
Cable color:	black
Terminal layout:	predefined by USB plug
	Subject to technical changes.

Ordering information

LECTUS enroll 5000 MD

Enrollment reader for reading the data record of Bosch coded MIFARE classic and DESFire EV1 credentials. Supported by host applications Access PE and BIS Access Engine. USB interface with 2m cable length, Dimensions 112 x 54 x 27 mm Order number ARD-EDMCV002-USB

Represented by:

Americas:

Americas: Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 security.sales@us.bosch.com www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V. P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2609 apr.securitysystems@bosch.com www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
203 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division Via Anhanguera, Km 98 CEP 13065-900 Campinas, Sao Paulo, Brazil Phone: +55 19 2103 2860 Fax: +55 19 2103 2862 latam.boschsecurity@bosch.com www.boschsecurity.com